

Amended
 column-direction data-transfer data line that has transferred the predetermined data and a row-direction data-transfer data line that has transferred the predetermined data.

IN THE CLAIMS:

Please replace claims 1-4 as follows:

1. (Amended) A high-speed vision sensor, comprising:

AS Cont
 a photodetector array having a plurality of photodetectors, which are arranged two-dimensionally in a plurality of rows and in a plurality of columns;

an analog-to-digital converter array having a plurality of analog-to-digital converters which are arranged one-dimensionally such that each analog-to-digital converter corresponds to one row in the photodetector array, each analog-to-digital converter converting, into digital signals, analog signals which are successively outputted from the photodetectors in the corresponding row;

a parallel processing system including a parallel processing element array, the parallel processing element array having a plurality of processing elements which are arranged two-dimensionally in a plurality of rows and in a plurality of columns and in one-to-one correspondence with the plurality of photodetectors in the photodetector array, each processing element performing a predetermined calculation on digital signals which are transferred from the analog-to-digital converter array;

a column-direction data-transfer bus including a plurality of column-direction data-transfer data lines which are arranged in one to one correspondence with the plurality of columns in the parallel processing system, each column-direction data-transfer data line being connected to the processing elements that are located in the corresponding column and performing data transfer operation with each processing element in the corresponding column;

a row-direction data-transfer bus including a plurality of row-direction data-transfer data lines which are arranged in one to one correspondence with the plurality of rows in the parallel processing system, each row-direction data-transfer data line being connected to the processing elements that are located in the corresponding row and performing data transfer operation with each processing element in the corresponding row; and

AS
cont
a control circuit controlling the photodetector array, the analog-to-digital converter array, the parallel processing system, the column-direction data-transfer bus, and the row-direction data-transfer bus, and performing data transfer operation with the processing elements via the column-direction data-transfer bus and the row-direction data-transfer bus, the control circuit controlling a combination of data to be transferred via each column-direction data-transfer data line to the corresponding processing elements and data to be transferred via each row-direction data-transfer data line to the corresponding processing elements, thereby controlling each processing element to perform a processing that is determined based on the combination of data received from the corresponding column-direction data-transfer data line and data received from the corresponding row-direction data-transfer data line.

2. (Amended) A high-speed vision sensor as claimed in claim 1, wherein the control circuit includes a center-of-gravity calculation control portion for controlling each column-direction data-transfer data line to perform data transfer operation to transfer data indicative of positional information of the corresponding column to the processing elements on the corresponding column, for controlling each row-direction data-transfer data line to perform data transfer operation to transfer data indicative of positional information of the corresponding row to the processing elements on the corresponding row, and for controlling each processing element to perform a predetermined calculation to calculate a center of

gravity of the digital signals based on the received data indicative of the positional information of the corresponding row and the received data indicative of the positional information of the corresponding column.

3. (Amended) A high-speed vision sensor as claimed in claim 1, wherein the control circuit includes a control portion for controlling a predetermined processing element to perform a predetermined calculation onto the digital signals by controlling a column-direction data-transfer data line that is connected to the predetermined processing element and a row-direction data-transfer data line that is connected to the predetermined processing element to perform data transfer operation to transfer a predetermined combination of calculation-control data.

4. (Amended) A high-speed vision sensor as claimed in claim 1, wherein the control circuit includes a data transfer control portion for controlling a column-direction data-transfer data line that is connected to a predetermined processing element and a row-direction data-transfer data line that is connected to the predetermined processing element to perform data transfer operation to transfer a predetermined combination of calculation-control data, thereby allowing calculation result data, obtained at the predetermined processing element, to be transferred to the control circuit.

Please add new claim 7 as follows:

-- 7. A high-speed vision sensor, comprising:

a photodetector array having a plurality of photodetectors, which are arranged two-dimensionally in a plurality of rows and in a plurality of columns;

an analog-to-digital converter array having a plurality of analog-to-digital converters which are arranged one-dimensionally such that each analog-to-digital converter corresponds

nal Stag

AS
CND

100-443887-100

a row-direction data-transfer bus including a plurality of row-direction data-transfer data lines which are arranged in one to one correspondence with the plurality of rows in the parallel processing system, each row-direction data-transfer data line being connected to the processing elements that are located in the corresponding row and performing data transfer operation with each processing element in the corresponding row; and

-9-